

# dB to % Power Loss

dB	Power Loss (%)	Power Transmitted (%)	dB	Power Loss (%)	Power Transmitted (%)	dB	Power Loss (%)	Power Transmitted (%)
0.000	0.00	100.0	1.50	29.20	70.80	6.00	74.88	25.12
0.001	0.02	99.98	1.60	30.81	69.19	7.00	80.05	19.95
0.01	0.20	99.80	1.70	32.39	67.61	8.00	84.15	15.85
0.05	1.00	99.0	1.80	33.93	66.07	9.00	87.41	12.59
0.10	2.00	98.0	1.90	35.43	64.57	10.0	90.00	10.0
0.20	4.50	95.5	2.00	36.93	63.07	11.0	92.06	7.94
0.30	7.00	93.0	2.10	38.34	61.66	12.0	93.69	6.31
0.40	9.00	91.0	2.20	39.74	60.26	13.0	94.99	5.01
0.50	11.0	89.0	2.30	41.11	58.89	14.0	96.02	3.98
0.60	13.0	87.0	2.40	42.45	57.55	15.0	96.84	3.16
0.70	15.0	85.0	2.50	43.76	56.24	16.0	97.50	2.50
0.80	17.0	83.0	2.60	45.04	54.96	17.0	98.00	2.00
0.90	19.0	81.0	2.70	46.29	53.71	18.0	98.40	1.60
1.00	20.56	79.44	2.80	47.51	52.49	19.0	98.70	1.30
1.10	22.37	77.63	2.90	48.71	51.29	20.0	99.00	1.00
1.20	24.14	75.86	3.00	49.88	50.12	30.0	99.90	0.10
1.30	25.86	74.14	4.00	60.19	39.81	40.0	99.99	0.01
1.40	27.55	72.45	5.00	68.38	31.62	50.0	99.999	0.001



10901 Telephone Trainer



28508 Physics of Fiber Optics Trainer



33503 Digital - Analog Lab



40628 Data Communication Trainer



46507 Three Phase Induction Motor Trainer



46514 Single Phase Induction Motor Lab



46609A Power Distribution Trainer



46800 Electrical Machine Trainer