

- Hand held 3½ digit Digital Multimeters with large LCD display incorporating latest technology.
- These Digital Multimeter can measure AC Voltage, DC Voltage, AC Current, DC Current, Resistance, Capacitance, Temperature and Frequency.
- Additional Features include Diode Test, Transistor check, Continuity check, Low Battery display, Data Hold and Auto Power Off.
- These Digital Multimeter have a built-in holster for anti sliding.



Test Leads



K-Type Thermocouple Lead

Model No:- 16963 /16964

FUNCTIONS	RANGE	BASIC ACCURACY	
		16963	16964
Voltage DC	200mV/2V/20V/200V/1000V	± (0.5%+3)	
Voltage AC	200mV/2V/20V/200V/750V	± (0.8%+3)	—
	2V/20V/200V/750V	—	± (0.8%+3)
Ampere DC	2mA /20mA/200mA/20A	± (0.8%+3)	—
	20mA/200mA/20A	—	± (0.8%+3)
Ampere AC	2mA/20mA/200mA/20A	± (1.0%+3)	—
	20mA/200mA/20A	—	± (1.0%+5)
Resistance	200Ω/2KΩ/20KΩ/200KΩ/2M / 20M /200M	± (0.8%+3)	
Capacitance	2nF/20nF/200nF/2μF/200μF	± (2.5%+20)	—
	2nF/20nF/200nF/2μF/20μF/200μF	—	± (2.5%+20)
Temperature	-40°C ~ 1000°C	—	± (0.8%+3)
Frequency	200KHz		± (1.5%+5)
SPECIAL FUNCTIONS			
Diode Testing		✓	✓
Continuity Test		✓	✓
On off warning		✓	✓
Low Battery display		✓	✓
Datahold		✓	✓
Auto Power off		✓	✓
Operating Mode	Manual range	✓	✓
Maximum Display	1999	✓	✓
Display Size	63mmX32mm	✓	✓
Power Supply	9V battery (6F22)	✓	✓

Accessories with the Meter

(With 16964 Only)

Note: Specifications are subject to change.

Tesca Technologies Pvt. Ltd.

IT-2013, Ramchandrapura Industrial Area, Sitapura Extension,
Near Bombay Hospital, Vidhani Circle, Jaipur-302022, Rajasthan, India,
Tel: +91-141-2771791 / 2771792; Email: info@tesca.in, tesca.technologies@gmail.com
Website: www.tesca.in

